

LINACT-SC-30 DC Speed Controller - 30A



The Compact DC Speed Controller allows you to control the speed of an actuator by rotation of a control knob. The unit will not increase the speed of the actuator but will control the speed from the maximum rated speed to zero. This DC speed controller is rated for 30A. This is compatible with all our actuator models and can be combined with rocker switch.

Product Specifications

Input Voltage:	12V, 24V, 36V
Current:	30A

Note:

1. DC motor controller input is connected to direct current, *cannot* be connected to alternating current, or it will be damaged and burnt.
2. Make sure the positive and negative polarity is connected correctly, otherwise the controller will be damaged.
3. The motor can be divided into positive and negative poles. When the running direction is inconsistent with the desired direction, the direction can be changed by swapping the wires.
4. The potentiometer knob can change the governor output duty cycle to change the motor speed.